

16V Dual Channel, Load Switch and LDO

1 Description

The AL783 is a power management unit that integrates a load switch and a low noise, low dropout linear regulator for 12V input power supplies. The load switch is capable of supporting up to 1A output current, while the LDO provides 160mA output current with adjustable output voltage. The AL783 ensures reliability with independent output short-circuit protection for each channel, thermal protection and input under-voltage lockout function, and input over-voltage protection.

The AL783 is available in SOT23-6 and SOP8 packages. A compact solution is available with minimal external components.



2 Features

- Low power consumption: quiescent current: 125uA
- Wide input voltage range: 5-16V
- Channel I : Adjustable Current Limit Load Switch
- Channel II : 160mA current limited LDO with adjustable output voltage
- Channel II output voltage accuracy of 2%
- Input overvoltage protection: 22.5V
- Overcurrent protection for dual channel independent hiccup mode
- Short circuit protection for dual channel independent hiccup mode
- Thermal shutdown
- Supports SOP8 and SOT23-6 packages.

3 Applications

- Smart Meters
- Portable Battery Powered Devices
- IP camera

4 Pinout




5 Ordering information

| Product Number | Package | Quantity/ Tape |
|----------------|---------|-------------------|
| AL783S | SOP8 | 4000/Tape |
| | | |
| AL783 | SOT23-6 | 3000/Tape |
| | | |

备注：丝印第一行表示规格型号，第二行表示批号（如 2115，表示 2021 年 15 周）


6 Typical Application



7 Pin Descriptions

| Pin No. | | Pin Name | Descriptions |
|---------|------|----------|--|
| SOT23-6 | SOP8 | | |
| 1 | 8 | OUT | Load switch output pin. |
| 2 | 6 | GND | Ground. |
| 3 | 7 | FB | AL783: LDO output voltage feedback pin. FB detects the output voltage of the LDO, which is regulated to 1.1V by the control loop, and a resistor divider is connected at FB. |
| 4 | 3 | LDOOUT | LDO output pin. |
| 5 | 2 | ISET | Current Limit Setting Pin. The current limit of the load switch can be programmed by connecting a resistor between the ISET pin and the GND pin. The current limit is typically 530mA when ISET is short to ground or floated. |
| 6 | 1 | VIN | Input pin. |
| | 4 | NC | No connect. |
| | 5 | NC | No connect. |

8 Block Diagram



9 Specifications

9.1 Absolute Maximum Ratings

| Parameter | Symbol | Value | Units |
|----------------------|--------------|----------|-------|
| Input voltage | V_{IN} | -0.3~24 | V |
| Output voltage Range | V_{OUT} | -0.3~24 | V |
| ISET voltage | V_{ISET} | -0.3~6 | V |
| FB voltage | V_{FB} | -0.3-6 | V |
| LDO Output Voltage | V_{LDOOUT} | -0.3-12 | V |
| Storage temperature | T_{stg} | -55~+150 | °C |

9.2 ESD Ratings

| Discharge mode | Standard | Value | Units |
|----------------|-----------------------------|-------|-------|
| HBM | ANSI/ESDA/JEDEC JS-001-2024 | ±3000 | V |
| CDM | ANSI/ESDA/JEDEC JS-002-2022 | ±2000 | V |
| Latch up | JESD78F.02-2023 | ±200 | mA |

9.3 Recommended Operating Range

| Parameter | Symbol | Min. | Max. | Units |
|--------------------------|-----------------|------|------|-------|
| Input voltage range | V _{IN} | 5 | 16 | V |
| LDO Output Voltage Range | VLDOOUT | 1.8 | 7 | V |
| Operating Temperature | T _A | -40 | 85 | °C |

9.4 Thermal Information

| Parameter | Package | Value | Unit |
|---|---------|-------|------|
| Junction to ambient thermal resistance(θ_{JA}) | SOT23-6 | 220 | °C/W |
| Junction to ambient thermal resistance(θ_{JA}) | SOP8 | 110 | °C/W |


9.5 Electrical Characteristics


Test conditions: $V_{IN}=12V$, $T_A=25^{\circ}C$, unless otherwise specified.

| Parameter | Symbol | Conditions | Min | Typ | Max | Unit |
|--|----------------------|---|--------------|------|--------------|-------------|
| Input Voltage Range | V_{IN} | | 5 | | 16 | V |
| Quiescent Current | I_Q | | | 125 | | μA |
| Input UVLO Threshold | V_{IN_UVLO} | VIN rising | | 4.6 | | V |
| Input UVLO hysteresis | $V_{IN_UVLO_HYST}$ | VIN falling | | 0.3 | | V |
| Input OVP Threshold | V_{IN_OVLO} | VIN rising | | 22.5 | | V |
| Input OVP hysteresis | $V_{IN_OVLO_HYST}$ | VIN falling | | 1 | | V |
| Load Switch On-resistance | R_{DSON} | IOUT=1A, OCP threshold setting greater than 1.2A | | 370 | | m Ω |
| Load Switch Current Limit | I_{LIM_OUT} | Rlimit=200K Ω | | 0.15 | | A |
| | | Rlimit=10K Ω | | 1.1 | | A |
| | | Float ISET pin | | 0.53 | | A |
| Load Switch Short Circuit Current Limit | | OUT short to GND | | 0.09 | | A |
| LDO Output Voltage Accuracy | | Internal integrated voltage divider resistor | -2 | | 2 | % |
| FB Voltage Accuracy | | AL783 | 1.1*0.9 8 | 1.1 | 1.1*1.0 2 | V |
| LDO Dropout Voltage | V_{DROP} | $I_{LDOOUT}=100mA@V_{OUT}=5V$ | | 90 | | mV |
| LDO Current Limit | I_{LIMIT_LDO} | | 160 | 220 | | mA |
| OUT Short Circuit Detection Time | T_{dect_OUT} | | | 211 | | ms |
| OUT short-circuit hiccup interval | T_{hicup_OUT} | | | 3.24 | | s |
| LDOOUT short-circuit detection time | T_{dect_LDOOUT} | | | 53 | | ms |
| LDOOUT short-circuit hiccup interval time | T_{hicup_LDOOUT} | | | 0.81 | | s |
| Overtemperature protection point | T_{TSD_OUT} | | | 160 | | $^{\circ}C$ |
| Over-temperature protection hysteresis | T_{TSD_HYST} | | | 30 | | $^{\circ}C$ |

9.6 Characteristics Curve (AL783)

Test conditions: $V_{IN}=12V$, $T_A=25^{\circ}C$, unless otherwise specified.





10 Detailed Description

10.1 Overview

The AL783 is a PMU that integrates a load switch and a low noise LDO, with the Channel I load switch providing up to 1A output current and the Channel II LDO regulator providing up to 160mA output current.

The AL783 is available in LDO fixed output version AL783XX and LDO adjustable output version AL783

10.2 Current Limit Protection


The AL783 contains two independent current limit circuits for monitoring and controlling the gate voltage of the pass transistors to limit the output current to a certain value. The current limit of the LDO is fixed at 220mA, and the current limit of the load switch can be set by the external resistor R_{limit} on the ISET pin. Once the load switch output current reaches the current limit threshold, the internal circuit regulates the gate voltage to maintain a constant power MOSFET current. In order to limit the current, the gate-to-source voltage must be regulated from 5V to about 1V. Typical response time is about 15 μ s, during which a small overshoot of the output current may occur. the AL783 allows the ILIMIT pin to be floated or shorted to ground during operation. The AL783 allows the ILIMIT pin to be floated or shorted to ground during operation. If the ILIMIT pin is floated or shorted to ground, the current limit is internally set to 530mA.

10.3 Short Circuit Protection

The AL783 incorporates an independent short-circuit protection function. If the load current increases rapidly due to a short circuit, the current may exceed the current limit threshold before the control loop reacts. when the current exceeds 1.5 times of the current limit value, the short circuit protection function will be triggered and the fast shutdown circuit will be activated to shut down the power MOSFET. when the chip triggers the short circuit protection, it will be restarted once for checking whether the short circuit exists. If the short circuit still exists when the device is restarted, the AL783 will adjust the gate voltage to keep the current at the short-circuit current limit level. If the short-circuit condition at the OUT pin remains for more than 210 ms, the IC enters hiccup mode and the power FETs are forced off and enabled again after 3.2 s. If a short-circuit condition at the LDOOUT pin is maintained for more than 50 ms, the IC enters hiccup mode and the power FET is forced off and re-enabled after 0.8s.

10.4 Load Switch Fold Back Function

The AL783's load switch current limit protection integrates a fold back protection function. When the OUT voltage is less than 3.5V, the ILIMIT threshold decreases as the VOUT voltage decreases, with a downward slope of 400 mA/V, and the minimum current limit is the short-circuit current limit.



10.5 Input Overvoltage Protection

The AL783 will be disabled when the input voltage is greater than the protection threshold (typically 22.5 V) and will be enabled again when the input voltage drops below 21.5 V. The AL783 will be disabled when the input voltage falls below the protection threshold (typically 22.5 V).


10.6 Thermal Shutdown

The AL783 will go into thermal shutdown when its temperature rises above 160°C. It will only go into thermal shutdown when the temperature drops below 130°C. The device will only be reactivated when the temperature drops below 130°C. The AL783 will not be reactivated until the temperature has dropped to below 130°C.

11 Application information

11.1 Typical applications

The following figure shows a typical application schematic for a circuit that can be used to evaluate the performance of the AL783.



11.2 LDO Output Voltage Setting

For AL783 version, its LDO channel output voltage can be set by external feedback resistor, and the output voltage is calculated as follows:

$$V_{OUT} = V_{FB} \times \left(1 + \frac{R_2}{R_1}\right)$$

where V_{FB} is typically 1.1V typical (internal reference voltage).

11.3 Load Switch Current Limit Setting

The current limit value of the load switch can be set by the external resistor R_{limit} on the ISET pin. The formula for calculating I_{LIMIT} is as follows:

$$I_{LIMIT} = \frac{10K}{R_{limit}} + I_{LIMIT_SHORT}$$

Where I_{LIMIT_SHORT} is the short-circuit current limit, typical value is 90mA.

When the ISET pin is floating or shorted to ground, the current limit is set internally to 530mA.


11.4 PCB Layout

An efficient layout is essential for stable operation. For best results, refer to the diagram below and follow these guidelines


- Place the high current paths (VIN and VOUT) close to the device, using short, straight and wide leads.
- Place the input capacitors close to the VIN and GND pins.
- Connect VIN and VOUT pads to large VIN and VOUT planes to improve thermal performance.
- Place a current limiting resistor externally near the ISET pin pads.


11.5 Basic Performance

Test conditions: $V_{IN}=12V$, $T_A=25^{\circ}C$, unless otherwise specified.



11.6 Operating waveforms






OVP




OVP recovery




Load Switch short circuit protection



Load Switch short circuit protection recovery



LDO short circuit protection



LDO short circuit protection recovery

SOP-8L

unit: mm

